

**Part 1 General**

**1.1 SECTION INCLUDES**

- .1 Materials and installation for wire and box connectors.

**1.2 REFERENCES**

- .1 Canadian Standards Association (CSA International)
  - .1 CAN/CSA-C22.2No.18-98, Outlet Boxes, Conduit Boxes, Fittings and Associated Hardware.
  - .2 CSA C22.2No.65-93(R1999), Wire Connectors.
- .2 Electrical and Electronic Manufacturers' Association of Canada (EEMAC)
  - .1 EEMAC 1Y-2, 1961 Bushing Stud Connectors and Aluminum Adapters (1200 Ampere Maximum Rating).
- .3 National Electrical Manufacturers Association (NEMA)

**Part 2 Products**

**2.1 MATERIALS**

- .1 Pressure type wire connectors to: CSA C22.2 No.65, with current carrying parts of copper or copper alloy sized to fit copper or aluminum conductors as required.
- .2 Fixture type splicing connectors to: CSA C22.2 No.65, with current carrying parts of copper or copper alloy sized to fit copper conductors 10 AWG or less.
- .3 Clamps or connectors for armoured cable, aluminum sheathed cable, flexible conduit, non-metallic sheathed cable as required to: CAN/CSA-C22.2 No.18.Execution

**2.2 INSTALLATION**

- .1 Remove insulation carefully from ends of conductors and:
  - .1 Apply coat of zinc joint compound on aluminum conductors prior to installation of connectors.
  - .2 Install mechanical pressure type connectors and tighten screws with appropriate compression tool recommended by manufacturer. Installation shall meet secureness tests in accordance with CSA C22.2No.65.
  - .3 Install fixture type connectors and tighten. Replace insulating cap.
  - .4 Install bushing stud connectors in accordance with NEMA.

**END OF SECTION**