PANEL 'A' MOUNTING SURFACE LOCATION MECH. ROOM					MAI	TAGE N BUS ARKS	
DESCRIPTION	BKR	CIF	SCI	IIT	BKR		DESCRIPTION
HEATED CCTV ENCLOSURE & MONITOR	30	1 —	Ĭ	-22		SPACE	DESCRIPTION
HEATED CCTV ENCLOSURE & MONITOR	30	2 —	Ц			SPACE	
HEATED CCTV ENCLOSURE & MONITOR	30	3 -		—24		— IF—1	
HEATED CCTV ENCLOSURE & MONITOR	30	4 —	Ц	—25		#10 WIF	RF
SPARE	15	5 —	Ц	26		IF−1	\\
SPARE	15	6 —	Ц	<u>-27</u>		#10 WIF	
SPARE	15	7 -	Ц		40 -		
SPARE	15	8 —	Ц	<u>29</u>		#10 WIF	RF .
SPARE	15	9 —	Ц	30		SPACE	\ \mathrea{\pi_0}
SPARE	15	10—		31			
SPACE	_	11—	Ц	<del></del> 32		#10 WIF	RE
SPACE	_	12-	H	<b>—</b> 33	40 -	″ ¬_ IF−1	
SPACE	_	13—	4	<del>34</del>		#10 WIF	RE
SPACE	<b>-</b>	14-	<b>L</b> ↓	<b>—</b> 35	40 -	 ¬_ IF−1	
SPACE	<b>1</b> -	15—	4	<del></del> 36		#10 WIF	
SPACE	_	16-	H	<b>—</b> 37	40 -	 ¬ IF−1	
SPACE	_	17—	H	<del></del> 38		<b> </b>	RE
SPACE	_	18-	<b>├</b>	<b>—</b> 39	40 -	—————————————————————————————————————	
PANEL L	200	19—	lack	<del>4</del> 0		<b> </b>	RE
		20—	H	<b>—</b> 41	15 -	 ¬ EF−1	
		21—	Ш	<del>4</del> 2			

PANEL 'A' MOUNTING SURFACE			MAI	LTAGE 120/240V-1PH-3W IN BUS 400A
LOCATION MECH.		I OIDOUIT		MARKS TUB 2
DESCRIPTIO  EF-1	N BKF		BKR	DESCRIPTION  EF-2
Er-I	T 15		-	
		44 65		#10 WIRE
EF-1	15	45 66		EF-3
	L	46 67	1	#10 WIRE
EF-1	15	47-4-68	15	CROSSING GATE
		48 69	15	EBDD (x2)
EF-1	r <del>-</del> 15	49 70	15	EBDD (x2)
		50 7	15	MTS PANEL
EF-1	15	51 72	15	SC RECEPTACLE
	L.	52 73	5 -	SPACE
EF-1	<sub>-</sub> 15	53 74	-	SPACE
		5475	15	GF RECEPTACLES
EF-1	r 15	55 76	15	RECEPTACLES
		56 77	15	FIRE ALARM PANEL
EF-1	15	57 78	15	DVR
		58 79	30 -	UNIT HEATER
EF-1	15	59 80	- I	#10 WIRE
		60 8	_	SPACE
IR-1 (x4)	15	61 82	15	TRANSIT EXTERIOR SIGNAGE
IR-1 (x4)	15	62 83	15	TRANSIT EXTERIOR SIGNAGE
AUTOMATIC DOOR OPERATO	ORS (x2) 15	63 84		SPACE


PANEL 'L' MOUNTING SURFACE LOCATION MECH. ROOM		,			MAI REM	N BUS IARKS	120/240V-1PH-3W 200A LIGHTING CONTROL PANEL
DESCRIPTION	BKR	CI	RC	<u>UIT</u>	BKR		DESCRIPTION
N/L LIGHTING	15	1 -	1	_22	15	EXTERIO	R LIGHTING
N/L LIGHTING	15	2 -	+	_23	15	EXTERIO	R LIGHTING
LIGHTING	15	3 —	${\sf H}$	-24	15	EXTERIO	R LIGHTING
LIGHTING	15	4 -	╟	25	15	EXTERIO	R SIGNAGE
LIGHTING	15	5 <b>—</b>	┢	26	15	EXTERIO	R SIGNAGE
LIGHTING	15	6 —	₩	27	15	SIGNAGE	
LIGHTING	15	7 -	╟	28	15	SIGNAGE	
LIGHTING	15	8 -	+	29	-	SPACE	
LIGHTING	15	9 —	H	30	_	SPACE	
LIGHTING	15	10-	╟	31	_	SPACE	
LIGHTING	15	11 —	+	32	_	SPACE	
LIGHTING	15	12-	H	33	_	SPACE	
LIGHTING	15	13 <b>-</b> €	+	34	_	SPACE	
LIGHTING	15	14-	┢	35		SPACE	
LIGHTING	15	15—	H	-36	-	SPACE	
EXTERIOR LIGHTING	15	16-	4	37	_	SPACE	
EXTERIOR LIGHTING	15	17—	+	38	_	SPACE	
CANOPY LIGHTING	15	18—	$\mathbb{H}$	-39	15	SPARE	
STEP LIGHTS	15	19-	+	40	15	SPARE	
POST LIGHTS	15	20—	+	41	15	SPARE	
EXTERIOR LIGHTING	15	21-	H	42	15	SPARE	

## HEATING SCHEDULE

TYPE	WATTS	VOLTAGE	DESCRIPTION	MANUFACTURER	CATALOGUE #	REMARK
UH-1	5000	240V-1PH	UNIT HEATER	CHROMALOX	EUH05B31T	NOTE 1

## SPECIFIC HEATING NOTES

1. C/W BUILT-IN THERMOSTAT. MOUNT SECURELY WHERE INDICATED TO THE SATISFACTION OF THE ENGINEER. (GENERAL) VOLTAGE TO BE AS INDICATED ABOVE UNLESS OTHERWISE NOTED ON DRAWINGS. (GENERAL) APPROVED EQUAL: OUELLET.



- SPECIFIC NOTES
- 1. WIRE AND CONNECT AS REQUIRED. REFER TO MECHANICAL.
  2. MAGNETIC STARTER BY DIV. 16.
- 3. MANUAL STARTER BY DIV. 16. 4. WIRE ALL CONTROL ALARMS AS REQUIRED (SEE MECHANICAL).

- A. MANUAL STARTERS TO BE C/W OVERCURRENT PROTECTION.
- B. ALL DISCONNECT SWITCHES TO BE SUPPLIED BY DIV. 16. C. ELECTRICAL CONTRACTOR TO PROVIDE CIRCUIT BREAKERS AND WIRING ACCORDING TO THE FINAL
- NAMEPLATES OF ALL THE MECHANICAL EQUIPMENT. ALL LOW VOLTAGE CONTROL WIRING BY DIV. 15.
- E. ALL LINE VOLTAGE CONTROL WIRING BY DIV. 16 REFER TO MECHANICAL SECTION. COORDINATE EXACT REQUIREMENTS WITH DIV. 15.

SPECIFIC ELECTRICAL NOTES

7 METRE LONG TAIL.

ROADWAY.

1) FOR CONNECTION TO GROUND LOOP. PROVIDE

GROUND LOOP TO RUN INSIDE STRUCTURE ABOVE


TYPICAL CONNECTION TO STRUCTURAL COLUMN VIA CADWELD.

4 ALLOW ADEQUATE CABLE FOR CONNECTION TO ELECTRICAL SERVICE GROUND.

TYPICAL #4/0 BARE COPPER BURIED 1 METRE BELOW GRADE.

6 TYPICAL GROUND ROD - SEE GENERAL ELECTRICAL

7 #4/0 BARE COPPER RUN UP/DOWN COLUMNS AND OVER ROADBED IN CEILING STRUCTURE.



GENERAL ELECTRICAL NOTES

1. PROVIDE A GRID NETWORK TYPE OF GROUNDING

SYSTEM, AS SHOWN ON THIS DRAWING, HAVING A

MAXIMUM RESISTANCE OF FIVE (5) OHMS. AFTER

2. TAPS AND CONNECTIONS WHICH ARE NORMALLY INACCESSIBLE AFTER INSTALLATION SHALL BE MADE

STRANDED COPPER INSTALLED 3'-0" (910mm)

BELOW GRADE. NO MECHANICAL PROTÈCTION ÍS

TESTING WITH A GROUNDING MEGGER, WHERE NECESSARY, ADDITIONAL GROUND RODS SHALL BE


PROVIDED TO OBTAIN THIS RESISTANCE.

SHALL NOT BE USED.

## EMERGENCY LIGHTING AND SIGNAGE

1. CONDUCTORS SIZED TO MANUFACTURERS RECOMMENDATIONS.

- MAXIMUM 5% VOLTAGE DROP. 2. WIRE AND CONNECT DC TO ALL COMPONENTS.
- 3. PROVIDE 60 MINUTE CAPACITY UNDER FULL LOAD.
- 4. INTERLOCK WITH NORMAL LIGHTING CIRCUIT TO ACTIVATE EMERGENCY LIGHTING UPON LOSS OF NORMAL LIGHTING.



400A-120/240V-1PH-3W

TO UTILITY TRANSFORMER

USING A CADWELD CONNECTION TYPE "TA". SOLDER 400A-120/240V-1PH-3W SINGLE LINE DIAGRAM 3. GROUND RODS SHALL BE 3/4" (19mm) DIAMETER BY 10'-0" (3050mm) LONG COPPER WELD RODS INSTALLED 2'-6" (760mm) BELOW GRADE. GROUND CABLE FOR THE NETWORK SHALL BE #4/0 BARE

NOTE 1: PANEL 'L' IS TO BE ONE COMPLETE UNIT, INCLUDING CIRCUIT BREAKER (POWER) SECTION, RELAY (CONTROL) SECTION, CPU, AND SURGE SUPPRESSION.

400A-120/240V-1PH-3W

D---3-500MCM RW90 IN 3" C.

400A-2P FUSIBLE

FUSED @ 400A BUSS JJN FUSES

CURRENT LIMITING


——3-500мсм RW90 IN 3" C.

CTs AND METERING

PANEL 'A' 10KA SCIC

SURGE SUPPRESSION


DISCONNECT SWITCH



LUN	MINAIRE SCHEDULE		
TYPE	DESCRIPTION	CATALOG NUMBER	LAMPS
Α	8' FLUORESCENT SURFACE MOUNTED - IP65 RATED C/W 3" STEM	PEERLESS STATION	4-54W T5HO/8' SECTIO
В	4' FLUORESCENT	LITHONIA UNS	1-54W T5H0
1	STEP LIGHT MOUNTED IN POSTS - REFER TO LANDSCAPE ARCH DWGS	FC LIGHTING FCSL400	3-3W LED
2	HID FLOODLIGHT MTD. IN STRUCTURE - INDIRECT	LITHONIA WFL-2	1-150W MH
5	POST MOUNTED LIGHT C/W 18' POST (5" ROUND)	REBELLE CYL-003	1-150W MH
6	ROADWAY LIGHTING	HOLLOPHANE PREDATOR	1-100W HPS
32	EMERGENCY DOUBLE HEAD FIXTURE -VANDAL RESISTANT, WEATHERPROOF	SEE SPEC SECTION 26 52 01	2-20W MR16

## LUMINAIRE SCHEDULE NOTES:

- ALL FLUORESCENT BALLASTS TO BE ELECTRONIC, MB HYDRO "POWER SMART" APPROVED.
- ALL FLUORESCENT LAMPS TO BE 4100K & 85 CRI, UNLESS OTHERWISE NOTED.
- REFER ALSO TO SPECIFICATION SECTION 26 50 00.




4. SPARE

FIRE ALARM SYSTEM TROUBLE ZONES: ALARM ZONES: 1. TAMPER SWITCHES 2. SERVICE BUILDING 2. LOW TEMPERATURE SWITCH 3. SPRINKLER FLOW LOW PRESSURE SWITCH


C5-E2202-T

FIRE ALARM RISER DIAGRAM



	SUPV. U/G STRUCTURES COMMITTEE	DATE
	NOTE:	
•	LOCATION OF UNDERGROUND STRU SHOWN ARE BASED ON THE BEST I AVAILABLE. BUT NO GUARANTE THAT ALL EXISTING UTILITIES ARE	NFORMATIO E IS GIVE SHOWN O
	THAT THE GIVEN LOCATIONS A CONFIRMATION OF EXISTENCE A LOCATION OF ALL SERVICES OBTAINED FROM THE INDIVIDUA BEFORE PROCEEDING WITH CON	ND EXAC MUST B L UTILITIE

LOCATI UNDERG		APPROVED STRUCTURES	B.M. ELE				DESIGNED BY	ZOZZZ	ENGIN
						·	DRAWN BY	NOVA 3 ENGINEERING LTD. CONSULTING ENGINEERS	
SUPV. U/G S COMMITTEE	SIRUCIURES	DATE					CHECKED BY		3
NOTE:	F UNDERGROUI	ND STRUCTURES AS					APPROVED BY	DILLON	REU.
AVAILABLE.  THAT ALL EX THAT THE ( CONFIRMATION	BUT NO GUANISTING UTILIT GIVEN LOCATION OF EXIST	E BEST INFORMATION ARANTEE IS GIVEN IES ARE SHOWN OR IONS ARE EXACT. ENCE AND EXACT ENCE AND EXACT EVICES MUST BE DIVIDUAL UTILITIES IH CONSTRUCTION.					HOR. SCALE	RELEASED FOR CONSTRUCTION	
LOCATION OBTAINED F	OF ALL SEP ROM THE INI	RVICES MUST BE	1	ISSUED FOR TENDER	2010-05-14	DZ	VERTICAL		CONSU
BEFORE PRO	OCEEDING WI	IN CONSTRUCTION.	NO.	REVISIONS	DATE	BY	DATE	DATE	



088813

# THE CITY OF WINNIPEG TRANSIT DEPARTMENT Winnipeg

FIRE ALARM SYSTEM

CITY DRAWING NUMBER B237-10-93 SOUTHWEST RAPID TRANSIT CORRIDOR - STAGE 1 OSBORNE STATION & ASSOCIATED WORKS 93 °F 121 CONSULTANT DRAWING NUMBER ELECTRICAL DETAILS AND SCHEDULES

**gpp**architecture