





ELECTRICAL LEGEND	
TYPE	DESCRIPTION
\Leftrightarrow	DUPLEX RECEPTACLE
\$	LIGHT SWITCH, SINGLE POLE
\triangleright	DATA PORT
4	VOICE (PHONE) PORT
PNL	ELECTRICAL PANEL
₽ ₽	POWER POLE
N.RACK	NETWORK RACK WITH COMPONENTS

POWER AND SYSTEMS DEMOLITION NOTES: "("x")"

ALL ABANDONED CABLES TO BE REMOVED FROM PLENUM SPACES AS REQUIRED BY LATEST CANADIAN ELECTRICAL CODE. DO NOT DISTURB OR DISCONNECT ANY WIRING & CABLING IN AREA OF WORK REQUIRED FOR OTHER AREAS.

- 1. IN AREA OF WORK: REMOVE & DISCONNECT COMPONENTS WITH DESIGNATION "D" BACK TO SOURCE, UNLESS OTHERWISE NOTED INCLUDING;
- 1.1. ALL LUMINARIES & LIGHT SWITCHES (NOT SHOWN) BACK TO SOURCE.
- 1.2. ALL POWER & DATA (REMOVED BACK TO SOURCE) ON INTERIOR WALLS TO BE DEMOLISHED.
- 1.3. ALL NETWORK DATA CABLING IN WALL BACK TO SOURCE.
- 1.4. ALL POLE POLES WITH POWER & DATA BACK TO SOURCE.
- 1.5. ALL AUDIO/VIDEO CABLING NOT IN SERVICE BACK TO SOURCE.
- 1.6. ALL IBM TYPE (BNC) CABLING BACK TO SOURCE. 1.7. DOOR BELL SYSTEM (NOT SHOWN) BACK TO SOURCE.
- IN AREA OF WORK:
- 2.1. CIRCUITS CONNECTED TO ELECTRICAL PANEL IN UNIT TO REMAIN.
- 2.2. REMOVE PHONE CABLING WITH CONNECTORS FROM DEMOLISHED WALLS & COIL-UP & SECURE TO CEILING SPACE FOR REUSE.
- 3. DISCONNECT ALL CABLING TO NETWORK RACK. RETURN NETWORK RACK & MOUNTED COMPONENTS BACK TO CONTRACT ADMINISTRATOR.
- 4. ALL FIRE DETECTION/PREVENTION DEVICES TO REMAIN (E.G., CEILING HEAT DETECTORS, SMOKE DETECTORS, FIRE ALARM PULL STATIONS, COMBINATION HORN STROBES, EMERGENCY SIGN/LIGHTING).

THESE DRAWINGS SHALL NOT BE SCALED. CONSULT WITH CLIENT AND DESIGNER ON ANY

ALSO REFER TO ELECTRICAL SPECIFICATIONS.

SUBMISSION OF SITE MARK-UPS, AS-BUILTS, OPERATING & MAINTENANCE MANUALS AND OTHER SUPPORTING DOCUMENTS TO CLIENT ARE MANDATORY AT THE COMPLETION OF THIS PROJECT

THE CONTRACTOR SHALL VISIT THE SITE AND ENSURE ALL DIMENSIONS, DATUM, AND DETAILED INFORMATION SHOWN ARE CORRECT.

THE CONTRACTOR IS TO REVIEW AND COORDINATE ALL ARCHITECTURAL, MECHANICAL AND ELECTRICAL DRAWINGS FOR ADDITIONAL OPENINGS THROUGH FLOORS, WALLS, AND CEILINGS FOR DUCTS, PIPES & ELECTRICAL RISERS AND ALL OPENINGS NOT SHOWN ON DRAWINGS.

ALL OPENINGS THROUGH FIRE ASSEMBLIES INCLUDING FLOORS AND CEILINGS ARE TO BE FIRE STOPPED AND SEALED WITH ULC APPROVED FIRE STOPPING TO MAINTAIN THE INTEGRITY OF THE FIRE SEPARATION, AND PROVIDE A SMOKE-TIGHT BARRIER.

ALL PRODUCTS AND MATERIALS TO BE USED AND INSTALLED SHALL CONFORM WITH MANUFACTURER'S SPECIFICATIONS, APPLICABLE CODES AND AUTHORITY HAVING

THE CONTRACTOR SHALL BE RESPONSIBLE TO PATCH AND MAKE GOOD ALL EXISTING CONSTRUCTION AFFECTED BY THE REMOVAL OF ALL ITEMS FORMING PART OF THE RENOVATION WORK.

COMMERCIAL DUTY DUPLEX RECEPTACLES SHALL BE "DECORA" STYLE, WHITE & CSA APPROVED, C/W WHITE FACE PLATES MOUNTED 18" ABOVE FINISHED FLOOR OR OTHERWISE

LIGHT SWITCHES SHALL BE "DECORA" STYLE & MOUNTED 42" ABOVE FINISHED FLOOR OR OTHERWISE NOTED.

PROVIDE DYNA LABELS ON ALL SWITCHES, PORTS & RECEPTACLES. PANEL SCHEDULE SHALL

BE RETYPED TO REFLECT AS-BUILT CONDITIONS & INSERTED TO INSIDE OF ASSOCIATED PANEL

ALL ABANDONED (KNOWN & UNKNOWN) ELECTRICAL FIXTURES, COMPONENTS, RECEPTACLES &

DATA CABLING SHALL BE REMOVED BACK TO SOURCE & TERMINATED AS PER APPLICABLE CODES. IF APPLICABLE, THIS INCLUDES WIRING CONTAINED IN HEADER DUCTS IN-FLOOR.

RECONNECT & TEST ALL FIRE PREVENTION EQUIPMENT.

ASBESTOS MAYBE PRESENT BEHIND WALLS, CEILING SPACE & FLOORS. IF ASBESTOS & ANY HAZARDOUS MATERIAL IS FOUND, STOP WORK IMMEDIATELY & CONTACT CITY OF WINNIPEG, CENTRAL CONTROLS, Ph 204-986-2351.

CONFIDENTIAL

TO BE USE BY PERSONNEL WITH WINNIPEG POLICE SERVICE SECURITY CLEARANCE LEVEL 2.

REVISION/DESCRIPTION

DESIGNED DTA APPROVED DATE 2018.09.10 USER APPROVAL



PROJECT

THE CITY OF WINNIPEG PLANNING, PROPERTY AND
DEVELOPMENT DEPARTMENT
MUNICIPAL ACCOMMODATIONS DIVISION 3-65 GARRY STREET, R3C 4K4

FORMER POST OFFICE TOWER DOOR RECONFIGURATION AT

SKYWALK ENTRANCE TO WPS HQ 266 GRAHAM AVENUE

SHEET TITLE

PARTIAL SECOND FLOOR AND REFLECTED CEILING PLAN DEMOLITION

POWER AND SYSTEMS

AS SHOWN

DRAWING SHEET SIZE: A1 (841mm x 594mm) PLOT 1:1